## ■ MODEL AND SUFFIX CODES

Model	Suffix Codes		Description
EJA110E			Differential pressure transmitter
Output signal	-DJFG.		4 to 20 mA DC with digital communication (BRAIN protocol) 4 to 20 mA DC with digital communication (HART 5/HART 7 protocol)*1 Digital communication (FOUNDATION Fieldbus protocol, refer to GS 01C31T02-01EN) Digital communication (PROFIBUS PA protocol, refer to
Measurement span (capsule)  Wetted parts	F		GS 01C31T04-01EN)  0.5 to 5 kPa (2.0 to 20 inH <sub>2</sub> O) (For Wetted parts material code S)  0.5 to 10 kPa (2.0 to 40 inH <sub>2</sub> O)    (For Wetted parts material code M, H, T, A, D and B)  1 to 100 kPa (4 to 400 inH <sub>2</sub> O)  5 to 500 kPa (20 to 2000 inH <sub>2</sub> O)  0.14 to 14 MPa (20 to 2000 psi)  Refer to "Wetted Parts Material" Table.
material *2			Traise to Protect Fund Material Tuesday
Process connections  0			without process connector (Rc1/4 female on the cover flanges) with Rc1/4 female process connector with Rc1/2 female process connector with 1/4 NPT female process connector with 1/2 NPT female process connector with utprocess connector (1/4 NPT female on the cover flanges)
Bolts and nuts materia  G C			B7 carbon steel 316L SST 660 SST
Installation			Vertical piping, left side high pressure, and process connection downside Horizontal piping and right side high pressure Horizontal piping and left side high pressure Bottom Process Connection, left side high pressure*3*4 Universal flange*3
Amplifier housing 1			Cast aluminum alloy Cast aluminum alloy with corrosion resistance properties*5 ASTM CF-8M stainless steel*6
Description   Description		2	G1/2 female, one electrical connection without blind plugs 1/2 NPT female, two electrical connections without blind plugs M20 female, two electrical connections without blind plugs G1/2 female, two electrical connections and a blind plug <sup>*7</sup> 1/2 NPT female, two electrical connections and a blind plug <sup>*7</sup> M20 female, two electrical connections and a blind plug <sup>*7</sup> G1/2 female, two electrical connections and a SUS316 blind plug 1/2 NPT female, two electrical connections and a SUS316 blind plug M20 female, two electrical connections and a SUS316 blind plug
Integral indicator  □ D E N			Digital indicator*8 Digital indicator with the range setting switch*9 None
Mounting bracket  B D J K M			304 SST 2-inch pipe mounting, flat type (for horizontal piping) 304 SST 2-inch pipe mounting, L type (for vertical piping) 316 SST 2-inch pipe mounting, flat type (for horizontal piping) 316 SST 2-inch pipe mounting, L type (for vertical piping) 316 SST 2-inch pipe mounting (for bottom process connection type) None
Optional Codes			□/ Optional specification

The "▶" marks indicate the most typical selection for each specification.
\*1: HART 5 or HART 7 is selectable. Specify upon ordering.

- \*1: HART 5 or HART 7 is selectable. Specify upon ordering.
  \*2: \( \Delta\) Users must consider the characteristics of selected wetted parts material and the influence of process fluids. The use of inappropriate materials can result in the leakage of corrosive process fluids and cause injury to personnel and/or damage to plant facilities. It is also possible that the diaphragm itself can be damaged and that material from the broken diaphragm and the fill fluid can contaminate the user's process fluids.

Be very careful with highly corrosive process fluids such as hydrochloric acid, sulfuric acid, hydrogen sulfide, sodium hypochlorite, and high-temperature steam (150°C [302°F] or above). Contact Yokogawa for detailed information of the wetted parts material.

- \*3: Only applicable for Wetted parts material code S.
- \*4:
- Not applicable for measurement span code F.

  Not applicable for electrical connection code 0, 5, 7, 9 and A. Content rate of copper in the material is 0.03% or less and \*5: content rate of iron is 0.15% or less.
- \*6: Not applicable for electrical connection code 0, 5, 7 and 9.
- Material of a blind plug is aluminum alloy or 304 SST. Not applicable for output signal code G. \*7:
- \*8:
- Not applicable for output signal code F.