

Product Overview

SEAL 80-80

SEAL 80-80S

SEAL 80-81

SEAL 80-81S

SEAL 80-82

SEAL 80-8H



SEE - BELIEVETM

**80GHz High Frequency
Level Transmitter**

www.seeautomation.com

SEAL 80-80S

FMCW Radar Level Transmitter

SEE - BELIEVE™



Application	Liquid Measurement
Measuring Range	0~20m
Antenna Type	Lens /PTFE
Mounting Thread	Thread G1.5/Flange
Beam Angle	8°
Response Time	<0.6s (Due To Parameter Setting)
Medium Temperature	(-40~120) °C
DK Value Of Medium	>1.5
Process Pressure	(-0.1~2) MPa
Accuracy	<2mm
Signal Output	(4~20) mA HART
Working Frequency	(76 ~ 81) Ghz
Explosion Proof Grade	Ex ia IIC T6 Ga (Pending for Approval from Authority)


SEAL 80-80S

FMCW Radar Level Transmitter

SEE - BELIEVE™

Application	Code	Parameters		
Instrument Type	P	Standard		
	F	Explosion-Proof (Pending for Approval from Authority)		
Housing/ Protection Grade	L	Aluminum Alloy /IP68		
	G	Aluminum Alloy Dual Chamber/IP67		
	D	316L Stainless Steel /IP68		
	Y	Special Terms		
Antenna Type	2	Lens type/PTFE G1.5		
	3	Anti corrosion type		
Process Connection	G	Thread G1.5	A	Flange DN50
	J	Flange DN65	B	Flange DN80
	C	Flange DN100	Y	Special Terms
Electronic Unit	2	2 Wires (4~20) mA 24V DC/HART		
	3	4 Wires (4~20) mA 220V AC		
	Y	Special Terms		
Cable Inlet	M	M20*1.5	N	NPT1/2
Material Type	L	Liquid		
Range	1	(0~10)m		
	2	(0~20)m		
Special Custom	Y	Customized for a specific application		

Major Customers:



For any queries:

support@seeautomation.com | sales@seeautomation.com



See Automation & Engineers

Our Offices

Head Office:

Top Floor, A-8, Priyadarshani Vihar, Delhi, India - 110092
T: +91-11-22012324/4324 | +91-11-22017985 | M: +91-8178970947
E: support@seeautomation.com | sales@seeautomation.com |
W: www.seeautomation.com

Manufacturing Unit:

G44, Udyog Kunj Industrial Area, UPSIDC, Ghaziabad, India

www.seeautomation.com